



О продукте

Генераторные установки Go-Business обеспечивают оптимальную производительность, надежность и универсальность для систем выработки электроэнергии, резервных, основных и непрерывных приложений. Всесторонняя гарантия и послепродажная поддержка по всему миру. Возможна поставка запасных частей на 10 лет.

Мощность (kVA)

VOLTAJ	Standby Güç (ESP)		Prime Güç (PRP)		3 Faz, 50 Hz
	kW	kVA	kW	kVA	Amper
400/231	52,8	66,0	48	60,0	65

Stand By Rating (ESP): It is the way generators work at certain time intervals under variable load. It can work as backup power. It is not suitable to be operated under excessive load.

Prime Rating (PRP): It is the way of working as a continuous power supply when there is no mains power. When operating under variable load 24 hours a day, 10% overload is allowed for 1 hour every 12 hours.

общие черты

Наименование модели	GBYD-66
Частота (HZ)	50
Тип используемого топлива	Diesel
Марка и модель двигателя	YANGDONG Y4102ZLD
Марка и модель генератора	Business
Модель панели управления	D300
Кабина	GB-66

ХАРАКТЕРИСТИКИ ДВИГАТЕЛЯ

Двигатель	YANGDONG
инженерная модель	Y4102ZLD
Количество цилиндров (L)	4 cylinders - in line
дыра (mm.)	102
Инсульт (mm.)	118
Объем цилиндра (lt.)	3,8
воздухозаборник	Doğal Emişli
Коэффициент сжатия	18:1
Скорость (rpm)	1500

Емкость масла (Including Filter) (lt)	11,6
Резервная мощность (kW)	52,5
Премьер СИЛА (kW)	48
Количество рубашечных водонагревателей	1
Мощность водонагревателя в рубашке (Watts)	750
Используемый тип топлива	Euro Dizel
Впрыск и тип системы	Direct Enjeksiyonlu
Тип топливного насоса	Rotary Type
Губернатор система	механический
Рабочее напряжение (Vdc)	12 Vdc
Батарея и емкость(Quantity/Ah)	2x120
Зарядный генератор переменного тока	65
Способ охлаждения	Охлаждение водой
Емкость охлаждающей жидкости(Only with Engine / Radiator (lt)	6,8
Воздушный фильтр	Dry Type
Главный 100% Расход топлива под нагрузкой (lt/hour)	14,1
Главный 75% Расход топлива под нагрузкой (lt/hour)	12,9

Engine groups used in our products; Heavy-duty 4-stroke industrial diesel delivers reliable power, low emissions and quick response to load changes.

The standard integrated kit-mounted radiator system, designed and tested for engine cooling system rated ambient temperatures, simplifies plant design requirements for rejected heat.

Особенности генератора

Модель генератора	Business
Частота (HZ)	50
Сила (kVA)	66
напряжение (V)	400
Фаза	3
Автоматический регулятор напряжения	AS440
Регулирование напряжения	(+/-)1%
Система изоляции	H
Класс защиты	IP21 - IP23
Коэффициент мощности	0.8
Вес генератора переменного тока (Kg)	244
Охлаждающий воздух(m³/min)	15.7

2/3 step windings at low reactance; non-linear loads with low wave distortion, short-circuit possibility for troubleshooting and class H isolation.

Control System

The D-500 is an advanced generator control device that supports all types of communication and functionality. Its advanced communication features allow it to be included in any automation and monitoring system. The fact that all communication ports are available on the device and all of them are active at the same time is a revolutionary innovation in the sector.

Explanation

The advanced communication features of the device allow it to be integrated into any automation system. The complete software features of the device also allow software update via the USB port. Windows-based PC software allows programming and monitoring of the device via USB, RS-485, RS-232, Ethernet and GSM.

Main Features

- 400Hz generator support
- Event log with 400x measurement value
- All parameters can be changed from the front panel
- 3-level program password
- 128x64 pixel graphic LCD
- Language installation
- Current-voltage waveform
- Current-voltage harmonic analysis
- synchroscope and sync relay
- 16 Amp / 250V 5K / JK outputs
- 8 programmable digital inputs
- Entries can be increased to 40
- 8 programmable digital outputs
- Outputs can be increased to 40
- 4 programmable analog inputs
- CANBUS-J1939 & MPU input
- 3 programmed service alarms
- Multiple self-test program
- weekly work schedule
- Dual generator support, evenly aged
- Fine speed tuning (some ECUs)
- Automatic fuel pump control
- Protections cancellation feature
- Over power protection
- Reverse power protection
- Overcurrent IDMT protection
- load shedding, dummy load
- Multiple load shedding programs
- Current unbalance protection
- Voltage unbalance protection
- Fuel filling and fuel theft alarms
- Battery powered real time clock
- Idle speed control
- Battery charging work
- Battle mode support
- Multiple nominal requirement definitions
- Contactor+motorized switch driving
- 4 quarter energy meters
- Grid energy meters
- fuel meter
- fuel consumption meter
- Modem & ethernet pages
- Free configuration software

- Possibility of control via SMS
- Ready for central monitoring via Ethernet and GPRS
- Mobile generator support
- Automatic GSM geolocation
- GPS connection (USB and RS232)
- Dynamic DNS support
- Downloading software via USB
- IP65 protection with standard gasket

Functions

- AMF device (seamless)
- ATS device (seamless)
- Remote Start device
- Manual Operation device
- Motor Controller
- remote monitoring panel
- Long-term recording to flash memory
- Input-output boost

Communication

- Ethernet (10/100Mb)
- 4-band GPRS modem (optional)
- USB Host and USB Device
- RS-485 (2400-115200baud)
- RS-232 (2400-115200baud)
- Micro SD card slot
- J1939-CANBUS
- Geolocation via GSM
- GPS connection (USB and RS-232)
- Embedded web server
- Web monitoring and programming
- Central monitoring over the Internet
- SMS message sending
- Sending e-mail
- Freeware: Rainbow Plus
- Modbus RTU and Modbus TCP/IP
- SNMP

Remote Monitoring

- Single server supports 60'000 devices
- Provides data security, data is only sent to the server
- Use internet-based dynamic world map
- Device states are shown live on the map and side panel
- Hierarchical configuration and grouping
- Remote control of devices
- Supports all Datalogic devices connected with DKG 210 gateway
- Supports all brands of Modbus-enabled products with the DKG 210 gateway
- Data recording, analysis and reporting
- Tablet and smartphone interfaces



РАЗМЕРЫ ГЕНЕРАТОРА ОТКРЫТОГО ТИПА (mm)

длина	1800
ширина	850
высота	1240
СУХОЙ ВЕС (kg.)	850
ЕМКОСТЬ БАКА (lt.)	82

РАЗМЕРЫ КАБИНЫ ГЕНЕРАТОРА (mm)

длина	2300
ширина	1100
высота	1250
СУХОЙ ВЕС (kg.)	1210
ЕМКОСТЬ БАКА (lt.)	82



- Structure from sheet steel
- Emergency stop button
- The control panel is mounted on the chassis on the right.
- Corrosion resistant locks and hinges
- Oil drain line with valve on engine
- soundproofing materials
- Warehouse-Chassis

Go-Business Generator set cabins have the following features as standard;

- Compact design connection with weldless nuts and bolts.
- Integrally mounted cab, generator set, exhaust system and fuel tank.
- Housing made of steel components treated with polyester powder paint
- Easy access to all service points
- Exhaust system inside the cabin
- Wide doors on both sides
- Lockable control panel
- Emergency stop button mounted outside the cabin
- The fuel filler section and battery are only accessible via the lockable access doors.
- Customer options available to meet your application needs
- Noise level tests of Go-Business generator sets have been approved by Szutest (CE standards conformity assessment body) in accordance with 2000/14/EC directive.

Cabins

Optionally, it is possible to make protective and soundproof cabins against climatic conditions.

Chassis and Fuel Tank

It minimizes the vibration level thanks to its rigid structural design and anti-vibration wedges, which are made of steel with the feature and durability to carry the load of the generator set. All chassis contain lifting lugs. Except for the standard chassis, all of which are produced by Go-Business, special solutions designed in line with customer demands provide great convenience in transportation and placement. In generator sets with a power of less than 1600 kVA, the fuel tank is produced as integrated into the chassis. For generator sets with power greater than 1600 kVA, rectangular type fuel tank is provided separately with the generator set. Each type of fuel tank has a level indicator.